arXiv:1101.2766v1 [quant-ph] 14 Jan 2011

Passivity breaking of a local vacuum state in a quantum Hall system

Go Yusa,* Wataru Izumida, and Masahiro Hotta
Department of Physics, Tohoku University, Sendai 980-8578, Japan

(Dated: January 17, 2011)

We propose an experimental method for extracting the zero-point energy from a local vacuum state by performing local operations and classical communication (LOCC). We model a quantum Hall edge channel as a quantum entangled many-body channel and the zero-point fluctuation in the charge density of the channel as the vacuum state. We estimate the order of the energy gain using reasonable experimental parameters. Such a quantum feedback system breaks the passivity of a local vacuum state. It can be used to demonstrate Maxwell's demon or quantum energy teleportation in which no physical entity transports energy.

PACS numbers: 03.67.-a, 73.43.-f

According to quantum mechanics, a many-body system in the vacuum state possesses a zero-point energy. However, this must be considered a non-available resource since it is not possible to extract the zero-point energy from a vacuum by performing local operations ; this is known as the passivity of the vacuum state [1]. However, recent theoretical studies have suggested that the passivity can be broken *locally* by performing local measurements followed by local operations and classical communication (LOCC) *locally*[2]. This scheme can be interpreted in terms of information thermodynamics as a quantum version of Maxwell's demon [3]; specifically, two demons cooperatively extract energy from a local vacuum state. We consider a quantum entangled many-body system in the vacuum state. As mentioned above, the demons cannot extract energy from the system by performing local operations. Here, we define two subsystems A and B that are separated by an appropriate distance. Since local quantum fluctuations are entangled in the vacuum state [4], demon A can obtain a certain amount of information on quantum fluctuations at B by performing local measurements at A. However, in exchange for this information, demon A has to pay an energy E_A to his/her own subsystem. Immediately after demon A informs demon B of the information (i.e., the measurement result), demon B can extract energy E_B even though his/her subsystem remains in a local vacuum state. This is passivity breaking by LOCC. This scheme is called quantum energy teleportation (QET) because no actual carriers transfer energy from A to B but energy can be gained at a remote location B [2]. This type of quantum feedback is also relevant to black hole entropy, whose origin has often been discussed in string theory [5], because energy extraction from a black hole reduces the horizon area (i.e., the entropy of the black hole [6]).

To verify this theory in a realistic system requires a dissipationless quantum-entangled channel with a macroscopic correlation length, a detection scheme for the vacuum state, and a suitable implementation of LOCC. Quantum Hall systems are promising systems. They can be formed in a two-dimensional electron system in a semiconductor subjected to a strong perpendicular magnetic field. Such a system is suitable because the zero resistance of the quantum Hall effect means that the system is dissipationless and quasi-one-dimensional channels appear at the boundary of the bulk incompressible region of a quantum Hall system; such an edge channel is considered to behave as a chiral Luttinger liquid [7]. Power-law behaviors have been experimentally demonstrated, suggesting that the system has no certain decay length [8, 9]. Furthermore, since the vacuum is a zero-point fluctuation in the charge density, the Coulomb interaction (i.e., capacitive coupling), can be used as a sensitive probe for detecting the vacuum. In addition, semiconductor nanotechnology can be used to design LOCC.



FIG. 1. (color online). Schematic diagram of the quantum Hall system used in this study. Edge channels S and U are formed at the boundaries of separate quantum Hall bulk regions S and U, respectively. Red and blue arrows indicate the directions of propagating waves. W_U is a wavepacket excited in region U.

In this study, we discuss possible passivity breaking in a quantum Hall system and estimate the order of the energy gain at B by employing reasonable experimental parameters.

We consider the system depicted schematically in Fig. 1. Experiments should be performed at low temperatures of the order of millikelvins (mK) to produce these vacuum states in the edge channels. Two regions, A and B, are defined on the left-going edge channel S. We describe S by a chiral Luttinger boson field with the trajectory parameterized by a spatial coordinate x along the channel. Here, we consider the left-going chiral field whose electron number density $\varrho_S(x+v_g t)$ deviates from that of the vacuum state equilibrium. v_g is the group velocity of a charge density wave propagating along the channel (i.e., a magnetoplasmon [10] in the zero-energy limit) and t is the elapsed time. The zero-point fluctuation in the charge density in region A can be experimentally measured by an RC circuit that consists of the input resistance R of an amplifier and the capacitance C between S and a local metal gate fabricated on S. For positive operator valued measure (POVM) measurements [9], the RC circuit (i.e., the detector) can be switched on only during the measurement. $t = 0$ is defined as the time when the switch is turned on. During the measurement, the detector excites S and injects energy E_A into S. The measured voltage signal v is amplified and then communicated to region U to excite a wave packet W_U on the other edge channel U. We describe the trajectory of U by a right-going chiral boson field $\varrho_U(y - v_g t)$ parameterized by a spatial coordinate y with identical velocity v_g, which assumes that S and U are formed in the same manner. Thus, W_U travels along U carrying energy E_1 toward region B, where the two edge channels S and U approach each other. These channels are capacitively coupled only at B, where W_U interacts with the zero-point fluctuation of S. After the interaction, the energy carried by W_U changes from E_1 to E_2. If no information about v is communicated (i.e., W_U is created *independently* of signal v) W_U will inject energy to S due to the passivity of the vacuum state [1]. Thus, $E_B = E_2 - E_1$ will be negative. However, in our system, since W_U explicitly depends on v, the passivity is broken and E_B is positive; W_U gains positive energy from the zero-point fluctuation of S. In the following, we prove this fact theoretically and estimate E_B by setting the experimental parameters $v_g \sim 10^6$ m/s [11, 12], $R \sim 10$ kΩ [13], and $C \sim 10$ fF. The length b of regions U and B and the length of region A are approximated by a typical length scale of $l \sim 10$ μm.

We start the detailed discussion by modeling the edge channel S. The chiral field operators $\varrho_S(x)$ satisfy the commutation relation $[\varrho_S(x),\ \varrho_S(x')] = i\frac{\nu}{2\pi}\partial_x \delta(x - x')$. The energy density operator of $\varrho_S(x)$ is written as

$$\varepsilon_S(x) = \frac{\pi\hbar v_g}{\nu_S} : \varrho_S(x)^2 :,$$

where ν_S is the Landau level filling factor of S and :: denotes normal ordering, which causes the expectation value of $\varepsilon_S(x)$ to vanish for the vacuum state $|0_S\rangle$; $\langle 0_S|\varepsilon_S(x)|0_S\rangle = 0$. The free Hamiltonian of S is given by $H_S = \int_{-\infty}^{\infty} \varepsilon_S(x)dx$. The eigenvalue of $|0_S\rangle$ vanishes, $H_S|0_S\rangle = 0$. Taking region A for $x \in [a_-,\ a_+]$ we adopt the RC-circuit-detector model proposed by Fève *et al.* [14] to measure the voltage induced by the zero-point fluctuation of S. The charge fluctuation at A is estimated as

$$Q_S(t) = e\int_{-\infty}^{\infty} \varrho_S(x + v_g t)\, w_A(x) dx, \qquad (1)$$

with a window function $w_A(x)$, which we assume to be a Gaussian function with its maximum value and width being of the order of unity and l, respectively. In this model [14], the voltage between the detector contact and S is given by $V(t) = \frac{1}{C}[Q_S(t) - Q(t)]$, where $Q(t)$ is the charge on the capacitor. The quantum noise of the voltage $V(t = -0)$ is described by the operator $\hat{V}$

$$\hat{V} = -\sqrt{\frac{\hbar}{\pi R C^2}} \times \int_0^{\infty} d\omega \left[\frac{\sqrt{\omega}}{\omega - \frac{1}{iRC}} a_{in}(\omega) + \frac{\sqrt{\omega}}{\omega + \frac{1}{iRC}} a_{in}^{\dagger}(\omega)\right],$$

where $a_{in}(\omega)(a_{in}(\omega)^{\dagger})$ is the annihilation (creation) operator of excitation of a charge density wave in the detector circuit satisfying $\left[a_{in}(\omega),\ a_{in}(\omega')^{\dagger}\right] = \delta(\omega - \omega')$. Before the measurement (i.e., the signal input from S to the detector), $V(t = -0)$ equals $\hat{V}$. Using the fast detector condition ($RC \ll l/v_g$), the voltage after the measurement is computed as

$$V(t = +0) = \hat{V} + R\dot{Q}_S(0), \qquad (2)$$

where $R\dot{Q}_S(0)$ denotes the voltage shift induced by the signal and the dot of $\dot{Q}_S(0)$ indicates the time derivative. The amplitude ΔV of $\hat{V}$ in the vacuum state $|0_{RC}\rangle$ of the RC circuit can be estimated as $\Delta V = \sqrt{\langle 0_{RC}|\hat{V}^2|0_{RC}\rangle} = O\left(\sqrt{\frac{\hbar}{RC^2}}\right) \sim 10$ μV. The root mean square of the voltage shift, $\sqrt{\langle 0_S|\left(R\dot{Q}_S(0)\right)^2|0_S\rangle}$, is estimated to be $O(100\ \mu\mathrm{V})$ from Eq. (1), so quantum fluctuations of the edge current will be detectable.

To estimate the energy injected into A after the measurement, we reduce the measurement operators [9] to the pointer basis of von Neumann [15]. By regarding $\hat{V}$ as a preamplified quantum pointer operator, the instantaneous shift in Eq. (2) can be reproduced by the measurement Hamiltonian, $H_m(t) = \delta(t)R\dot{Q}_S(0)P_{\hat{V}}$, where $P_{\hat{V}}$ is the conjugate momentum operator of $\hat{V}$. Using the eigenvalue v of $\hat{V}$ ($\hat{V}|v\rangle = v|v\rangle$), we can assume the initial wavefunction of the quantum pointer in the v representation to be $\Psi_i(v) \propto \exp\left[-\frac{1}{4\Delta V^2}v^2\right]$, whereas the wavefunction after the measurement is translated as $\Psi_f(v) \propto \exp\left[-\frac{1}{4\Delta V^2}\left(v - R\dot{Q}_S(0)\right)^2\right]$. After turning the measurement interaction on, we perform a projective measurement of $\hat{V}$ to obtain an eigenvalue v of $\hat{V}$.

This reduction analysis proves that the measurement operator M_υ [16] is $\Psi_f(\upsilon)$. The corresponding POVM is represented by the operator $\Pi_\upsilon = M_\upsilon^\dagger M_\upsilon$, which satisfies the standard sum rule, $\int_{-\infty}^{\infty} \Pi_\upsilon d\upsilon = I_S$, where I_S is the identity operator of the Hilbert space of S. The probability density of the result υ is $p(\upsilon) = \langle 0_S|\Pi_\upsilon|0_S\rangle$. The post-measurement state of S corresponding to the result υ is computed to be $M_\upsilon|0_S\rangle$ up to a normalization constant. Hence, the average state of S right after the measurement is given by

$$\rho_1 = \int_{-\infty}^{\infty} M_\upsilon|0_S\rangle\langle 0_S|M_\upsilon^\dagger d\upsilon.$$

The injected energy E_A is calculated to be

$$\begin{aligned} E_A &= \int_{-\infty}^{\infty} \langle 0_S|M_\upsilon^\dagger H_S M_\upsilon|0_S\rangle d\upsilon \\ &= \frac{\hbar v_g \nu_S}{4\pi}\left(\frac{e v_g R}{2\Delta V}\right)^2 \int_{-\infty}^{\infty} dx \left(\partial_x^2 w_A(x)\right)^2 . \end{aligned}$$

Using the experimental parameters mentioned above, E_A is estimated to be of the order of 1 meV for $\nu_S \sim 3$.

We now consider the edge channel U. The free Hamiltonian of U is $H_U = \frac{\pi\hbar \upsilon}{\nu_U}\int_{-\infty}^{\infty} : \varrho_U\left(y\right)^2 : dy$. The measurement result υ is amplified and transferred to region U as an electrical signal and it then generates a wave packet W_U of $\varrho_U(y)$ (i.e., a localized right-going coherent state) in a region with $y \in [b_- - L,\ b_+ - L]$. This process can be expressed by the υ-dependent unitary operation U_υ to the vacuum state $|0_U\rangle$ of $\varrho_U(y)$; $|\upsilon_U\rangle = U_\upsilon|0_U\rangle$. U_υ is given by

$$U_\upsilon = \exp\left(\frac{\pi i \upsilon}{\nu_U \Delta V}\int_{b_- - L}^{b_+ - L} \lambda_B(y)\varrho_U\left(y\right) dy\right),$$

where L is the distance between regions U and B and ν_U is the filling factor of U. Here, the length $b_+ - b_- = b$ is approximated by l. We assume that $\lambda_B(y)$ is a Gaussian function whose maximum, $\lambda_B(b/2 - L)$, gives the order of the total number of excess and deficient electrons from the vacuum-state equilibrium in $[b_- - L,\ b_+ - L]$, which are excited by the amplified voltage. We take the amplitude of $\lambda_B \sim O(10)$, which can be experimentally done by tuning the amplifier gain appropriately. By using $[\varrho_U(y),\ \varrho_U(y')] = -i\frac{\nu_U}{2\pi}\partial_y\delta(y - y')$, the wave form of W_U is computed as $\langle \upsilon_U|\varrho_U(y)|\upsilon_U\rangle = \upsilon\partial_y\lambda_B(y)$. By defining T as the elapsed time when W_U has been generated, the composite state of S and U at T is calculated as

$$\rho_{SU} = \int_{-\infty}^{\infty} d\upsilon U_S M_\upsilon|0_S\rangle\langle 0_S|M_\upsilon^\dagger U_S^\dagger \otimes |\upsilon_U\rangle\langle \upsilon_U|,$$

where $U_S(T) = \exp(-\frac{iT}{\hbar}H_S)$. This state is the scattering input state for the Coulomb interaction between S and U. Then, W_U evolves into region B by H_U. The average energy of W_U is denoted by $E_1 (= \mathrm{Tr}\left[H_B\rho_{SU}\right])$, which is calculated as

$$E_1 = \frac{\pi\hbar v_g}{\nu_U}\int_{-\infty}^{\infty}\left(\partial_y\lambda_B(y)\right)^2 dy\left[\langle 0_S|G_S^2|0_S\rangle + \frac{1}{4}\right],$$

where $G_S = -\frac{e v_g R}{2\Delta V}\int_{-\infty}^{\infty}\varrho_S\left(x\right)\partial_x w_A(x)dx$. E_1 is estimated to be of the order of 10 meV when ν_S and ν_U are respectively ~ 3 and ~ 6. In region B, W_U and $\varrho_S(x)$ interact with each other via the Coulomb interaction such that

$$H_{int} = \frac{e^2}{4\pi\epsilon}\int_{b_-}^{b_+} dx \int_{b_-}^{b_+} dy \varrho_S\left(x\right) f(x,y) \varrho_U\left(y\right).$$

Here, ϵ is $10\epsilon_0$ for the host semiconductor (e.g., gallium arsenide), where ϵ_0 is the dielectric constant of vacuum. The function $f(x,y)$ is given by $\frac{1}{\sqrt{(x-y)^2 + d^2}}$. Here, d is the separation length between the two edge channels at B and is approximated by l. After the interaction, the energy of W_U becomes E_2. The energy gain, $E_B = E_2 - E_1$, is estimated by lowest-order perturbation theory in terms of H_{int} as follows.

$$\begin{aligned} E_B = &-i\frac{e^2 v_g}{4\epsilon\nu_S}\int_{-\infty}^{\infty} dz \int_{b_-}^{b_+} dx_B \int_{b_-}^{b_+} dy_B f(x_B, y_B) \\ &\times \int_{-\infty}^{\infty} dt \int_{-\infty}^{\infty} d\upsilon \langle 0_S|M_\upsilon'^\dagger \varrho_S\left(x_B + v_g t\right) M_\upsilon'|0_S\rangle \\ &\times \langle \upsilon_U'|\left[\varrho_U\left(z - v_g t_f\right)^2,\ \varrho_U\left(y_B - v_g t\right)\right]|\upsilon_U'\rangle, \end{aligned}$$

where $M_\upsilon' = U_S(t_i - T)^\dagger M_\upsilon U_S(t_i - T)$ and $|\upsilon_U'\rangle = U_U(t_i)^\dagger|\upsilon_U\rangle$. Here, $U_U(T) = \exp(-\frac{iT}{\hbar}H_U)$. t_i and t_f are respectively the start and end times of the interaction between S and U. By substituting the commutation relation given by $\left[\varrho_U\left(z\right)^2,\ \varrho_U\left(y_B\right)\right] = -i\frac{\nu_U}{\pi}\partial\delta(z - y_B)\varrho_U\left(z\right)$ and integrating with respect to z, we obtain the following relation:

$$\begin{aligned} E_B = &\frac{e^2 v_g}{4\pi\epsilon}\int_{b_-}^{b_+} dx_B \int_{b_-}^{b_+} dy_B f(x_B, y_B) \\ &\times \int_{-\infty}^{\infty} dt \partial^2\lambda_B(y_B - v_g\left(t - t_i\right)) \\ &\times \int_{-\infty}^{\infty} \upsilon\langle 0_S|M_\upsilon'^\dagger \varrho_S\left(x_B + v_g t\right) M_\upsilon'|0_S\rangle d\upsilon. \end{aligned}$$

Note that the last integral is computed as

$$\begin{aligned} &\int_{-\infty}^{\infty} \upsilon\langle 0_S|M_\upsilon'^\dagger \varrho_S\left(x_B + v_g t\right) M_\upsilon'|0_S\rangle d\upsilon \\ &= -\frac{e\upsilon R}{4\Delta V}\int_{-\infty}^{\infty} d\bar{x}_A \partial w_A(\bar{x}_A) \\ &\times \Delta\left(\bar{x}_A - x_B - v_g(t + T - t_i)\right) + c.c., \end{aligned}$$

where

$$\Delta\left(x\right)=\frac{\nu_S}{4\pi^2}\int_0^\infty dkk\exp\left(-ikx\right).$$

To integrate E_B with respect to t, we take the Fourier transform of $\partial^2\lambda_B$ in E_B and obtain $\partial^2\lambda_B(y) = -\frac{1}{2\pi}\int_{-\infty}^{\infty} k'^2\tilde{\lambda}_B(k')e^{ik'y}dk'$. Using $\int_{-\infty}^{\infty} dt\exp[-i(k'\pm k)v_g t] = \frac{2\pi}{v_g}\delta(k'\pm k)$, E_B is estimated as

$$\begin{aligned}E_B=\frac{3e^3vR\nu_S}{4\pi^3\epsilon\Delta V}&\int_{-\infty}^{\infty}d\bar{x}_A\int_{b_-}^{b_+}d\bar{y}_B\int_{b_-}^{b_+}dx_B\int_{b_-}^{b_+}dy_B\\ &\times\frac{1}{\sqrt{\left(x_B-y_B\right)^2+d^2}}\\ &\times\frac{w_A(\bar{x}_A)\lambda_B(\bar{y}_B-L)}{\left(x_B+y_B-\bar{x}_A-\bar{y}_B+L+v_gT\right)^5},\end{aligned}$$

where $v_gT = O(10^{-2}L)$. The parameter $L + v_gT(= O(L))$ corresponds to the distance between A and B. Thus, the energy output E_B is estimated to be

$$E_B=O\left(\frac{e^2\lambda_B}{4\pi\epsilon l}\frac{ev_gR}{l\Delta V}\left(\frac{l}{L}\right)^5\right). \qquad (3)$$

Since the function $\lambda_B(\bar{y}_B + L)$ is positive, E_B must also be positive. Eq. (3) shows that increasing L will rapidly reduce the magnitude of E_B (e.g., $E_B \sim 1$ μeV for $L \sim 4l$). Nevertheless, for $L \sim 2l$, E_B will be of the order of 100 μeV. This is much larger than the thermal energy $\sim$ 1 μeV at a temperature of $\sim$ 10 mK, which is the temperature at which quantum Hall effect experiments are generally performed using a dilution refrigerator.

To observe E_B experimentally, we measure the current passing through the edge channel U. The relation, $\varepsilon = \frac{\pi\hbar}{\nu_U e^2 v_g}j^2$, between the energy density ε and the current j gives an energy density of 10-μeV/μm, which corresponds to a current of 10-nA. This can be detected experimentally using state-of-the-art electronics. To verify that energy is extracted at B, a single-shot current measurement should be repeated by switching the circuit on and off to perform POVM measurements a sufficient number of times to generate meaningful statistics. In this process, electrical noise, which can be introduced in the classical channel, is averaged out and thus does not affect $\langle E_B\rangle$.

We now examine energy conservation and dynamics in the system. As we have shown, extracting E_B from the local vacuum state requires measurement (energy injection) at A. What is the source of E_A? We consider a POVM measurement, so that switching the RC circuit injects an energy $E_A$into S. Therefore, a battery may provide $E_A$to drive the switching device if the switch is electrically operated. After extracting E_B, the total energy $E_A - E_B$of the system will be non-negative, as it should be because $E_A > E_B$. Due to local energy conservation laws, energy transfer of $E_B$from $S$to Uwill result in a negative average quantum energy density around B. This generation of a negative energy density is attained by squeezing the amplitude of the zero-point fluctuation less than that of the vacuum state during the interaction [17]. $-E_B$and $E_A$will run "chirally" on the edge toward the downstream electrical ground with identical velocities of v_g. Because of this chirality, even after measurement at region A, Saround region B will remain in a local vacuum state with zero energy density.

Unlike quantum Hall systems, several successful experimental studies have been conducted in quantum optics by introducing LOCC including quantum teleportation [18, 19]. Light is a massless electromagnetic field with an infinite correlation length. However, it propagates three dimensionally so that the energy gain decays rapidly with increasing distance between A and B. In addition, it is currently difficult to measure the vacuum state experimentally due to the lack of an appropriate interaction such as the Coulomb interaction in quantum Hall systems. Thus, our quantum Hall system is considered to be very suitable for demonstrating local vacuum passivity breaking.

In conclusion, we have theoretically demonstrated that the passivity of the vacuum can be locally broken by electrical LOCC in a realistic system using a quantum Hall edge channel as a many-body quantum channel.

The authors gratefully acknowledge K. Akiba and T. Yuge for fruitful discussions. G. Y., W. I., and M. H. are supported by Grants-in-Aid for Scientific Research (Nos. 21241024, 22740191, and 21244007, respectively) from the Ministry of Education, Culture, Sports, Science and Technology (MEXT), Japan. W. I. and M. H. are partly supported by the Global COE Program of MEXT, Japan. G. Y. is partly supported by the Sumitomo Foundation.

---

* yusa@m.tohoku.ac.jp

[1] W. Pusz and S. L. Woronowicz, Commun. Math. Phys. **58**, 273 (1978).

[2] M. Hotta, Phys. Lett. A **372**, 5671 (2008); M. Hotta, Phys. Rev. D **78**, 045006 (2008); M. Hotta, J. Phys. Soc. Jap. **78**, 034001 (2009).

[3] W. H. Zurek, in G. T. Moore and M. O. Scully, *Frontiers of Nonequilibrium Statistical Physics* (Plenum Press, New York), 151, (1984); S. Lloyd, Phys. Rev. A **56**, 3374 (1997); T. Sagawa and M. Ueda, Phys. Rev. Lett. **100**, 080403 (2008).

[4] B. Reznik, Found. Phys. **33,** 167 (2003); J. Silman and B. Reznik, Phys. Rev. A **71**, 054301 (2005).

[5] A. Strominger and C. Vafa, Phys. Lett. B **379**, 99 (1996); A. Sen, Gen. Rel. Grav. **40**, 2249 (2008).

[6] M. Hotta, Phys. Rev. D **81**, 044025 (2010).

[7] X. G. Wen, Phys. Rev. B **43**, 11025 (1991).

[8] M. Grayson *et al.*, Phys. Rev. Lett. **80**, 1062 (1998).

[9] A. M. Chang, L. N. Pfeiffer, and K. W. West, Phys. Rev. Lett. **77**, 2538 (1996).

[10] S. J. Allen, Jr., H. L. Störmer, and J. C. M. Hwang, Phys.

Rev. B **28**, 4875 (1983).

[11] R. C. Ashoori *et al.*, Phys. Rev. B **45**, 3894 (1992).

[12] H. Kamata *et al.*, Phys. Rev. B **81**, 085329 (2010).

[13] The characteristic impedance of wires is matched to R.

[14] G. Fève, P. Degiovanni, and Th. Jolicoeur, Phys. Rev. B **77**, 035308 (2008).

[15] J. von Neumann, "*Mathematical Foundations of Quantum Mechanics*", Princeton University Press, (1955).

[16] M. A. Nielsen and I. L. Chuang, "*Quantum Computation and Quantum Information*", Cambridge University Press, Cambridge, (2000).

[17] Such an emergence of negative energy density has been widely known in quantum field theory. For example, one of the most simple cases can be given with linear superposition of the vacuum state and multi-particle states of a quantum field [20].

[18] C.H. Bennett *et al.*, Phys. Rev. Lett. **70**, 1895 (1993).

[19] D. Bouwmeester *et al.*, Nature **390**, 575 (1997); A. Furusawa *et al.*, Science **282**, 706 (1998).

[20] L. H. Ford, Proc. R. Soc. London A **364**, 227 (1978).